

PFRS - SERVICE POST CONNECTOR WITH LAG SCREW

PFRS-35R-2C

Description

Purpose: Connection with COPPERSTEEL or copper cables. Used to align one or two downconductors on building facades (masonry or concrete). Use with nylon bushing S-10.

Characteristics: Tightening connection. High electrical conductivity and corrosion resistance.

Application: Grounding systems in general e lightning protection systems.

Material: Copper alloy.

Application Tool: Box open-ended or monkey wrenches.



Datasheet

Material	BRONZE
Qty. Of Conductors	2
Conductors - Cross Section (mm²)	
Mínimo	6 - 6
Máximo	35 - 35
Dimensions	
Figura	2
L	20,6
A	63,5
D	30,5
Rabicho - R	1/4* SOBERBA
Package	
Qtd / Emb	70
Peso Unit. (g)	47,00