

**PFRS - SERVICE POST CONNECTOR WITH LAG SCREW**

PFRS-70R-2C

**Description**

**Purpose:** Connection with COPPERSTEEL or copper cables. Used to align one or two downconductors on building facades (masonry or concrete). Use with nylon bushing S-10.

**Characteristics:** Tightening connection. High electrical conductivity and corrosion resistance.

**Application:** Grounding systems in general e lightning protection systems.

**Material:** Copper alloy.

**Application Tool:** Box open-ended or monkey wrenches.



**Datasheet**

|  |              |
|--|--------------|
| <b>Material</b>                                    | BRONZE       |
| <b>Qty. Of Conductors</b>                          | 2            |
| <b>Conductors - Cross Section (mm<sup>2</sup>)</b> |              |
| Mínimo   | 10 - 10      |
| Máximo   | 70 - 70      |
| <b>Dimensions</b>                                  |              |
| Figura   | 2            |
| L  | 27,0         |
| A  | 72,5         |
| D  | 30,5         |
| Rabicho - R  | 1/4* SOBERBA |
| <b>Package</b>                                     |              |
| Qtd / Emb  | 30           |
| Peso Unit. (g)                                     | 92,20        |